

WiFi Smart Socket User Manual

► Parameters

Wireless type:WiFi 2.4GHz 802.11b/g/n

Humidity:<80%

Material:ABS+PC

Rated voltage:AC 100-240V

Rated current:10A16A20A(Max)

Working Temp:-10℃-40℃

► Install the "Smart Life APP

- 1.You can download "Smart Life" app from Apple Appstore, Google Play, or scan the QR code below.



Smart Life APP

► Getting to Know "Smart Life" APP

1. Devices

You can list device by tap the "Home" Icon. If you want to add a device, please click the "+" icon in the upper right corner.

2.Switch

- A.You can press on/off button to turn on/off power.
- B. When the socket is connected to the network, you can use your smartphone to turn on and off the power.
- C.You can use an intelligent speaker to control the socket
- D. You can create scene to control sockets.

3.Timer

You can set the socket to turn on/off at the time you want

2. Enter the register / log in interface, input the phone number for getting the verification code to register an account.

►Connecting Your Socket with APP

- 1.Ensure that the socket is connected to the power, then Launch "Smart Life" APP, tap "ADD DEVICES" or "+" at the upper right corner of the page and select "Plug (BLE+Wi-Fi)";
- 2.Long press on/off button of the device for 5 seconds until indicator light flash quickly, the app in "Add Device" page.
- 3.Make sure the indicator light is flashing quickly and confirm it in app;
- 4.Choose the local WiFi and enter the correct password, and confirm;
5. Wait for configuring successfully, then tap "Done"

4.Countdown

Through the countdown function, you can turn on/off the power after the desired time.

5.Electricity statistics

If your device has energy monitoring function, you can view real-time and historical power consumption here

6.Scenes

With this function, you can create your characteristic asyou want.

7.Profile

Profile is the entrance for the users to manage personal information, mainly show the following information:

